



TRANSFORMER FOR LED SPOTS WARM WHITE

FUNCTION DESCRIPTION

Transformer for LED spots warm white with an operation current of 350 mA. You can connect up to 6 pieces of 1 W spots to one transformer (to dimmable transformer up to 15 spots). The connected spotlights can be dimmed by a poti at the control housing or by external 1 - 10 V dimming signal.

If more than 6 respectively 15 spots are required, a second light circuit has to be installed.



TECHNICAL DATA

	Dimmable transformer	Non-dimmable transformer
Electrical supply	230 V-AC, 50 - 60 Hz	
Power supply	42 VA	9 VA
Temperature range	0 to +50 °C	
Weight	1,2 kg	0,46 kg
Dimensions (W/H/D)	130 x 230 x 110 mm	100 x 80 x 65 mm

SCOPE OF DELIVERY

- Transformer installed in housing
- Poti for the manual dimming of the connected spotlights (at option dimmable transformer)
- 7 m cable from the controller to the 1st spot
- 1,5 m power supply cable with Euro plug

ACCESSORIES / OPTIONS

- Available with operation- / constant current 700 mA

